

BE-221H

2-port 雙屏 HD KVM Switch

BE-221H 是一台集雙屏 HD、音源、麥克風、USB 的 2-port 電腦切換器。透過它可以讓操作者使用一套鍵盤、滑鼠、雙螢幕來操作兩台電腦。



產品特性

- ❖ 只需一組鍵盤、滑鼠、螢幕、喇叭/麥克風即可操作兩台電腦並共享USB 2.0設備。
- ❖ 支援解析度4K60, 1920x1200@60, 1080p ...
- ❖ 操控端內建USB 2.0 HUB，可支援觸控、隨身碟...
- ❖ 操控端支援EDID學習功能。
- ❖ 提供按鈕(SELECT)與鍵盤兩種切換方式。
- ❖ 提供選購的RS-232切換套件。
- ❖ 支援外接3.5mm音源與麥克風功能。
- ❖ 支援Online與Select的狀態LED燈。
- ❖ 支援切換按鈕延長線。
- ❖ 熱插拔，不須安裝任何驅動軟體。

Panel Diagram

Front View



Rear View



Switching Button Extension Cable



Specifications:

		BE-221H
Computer Host Ports	HD-IN	2-port each Dual-HD Type A Female
	USB Upstream	2-port each USB-B
	Audio	2-port each 3.5mm Line-In (Green) and Microphone (Pink)
Console Ports	HD-OUT	2 x HD Type A Female
	USB-A	2 x USB 2.0 (Touch, Storage, ...) + 2 x USB 1.1 (keyboard, mouse)
	3.5mm Audio	1 x Line-Out (Green) + 1 x Microphone (Pink)
LED		2 x On Line status (Red) + 2 x Select (Green)
PC Selection		Front Panel SELECT button/Switching Button Extension Cable & keyboard hotkey
Keyboard Hotkey Selection		Ctrl + Ctrl / Scroll Lock+ Scroll Lock 1 or 2
RS-232 Selection Option		BE-601RS85 + RS-485-to-RS-232 adapter
Supported Resolutions		3840x2160@60Hz, 1920x1200@60Hz, 1080p, ...
Power Adapter		DC 5V, 1A
Temperature	Operating	-10 ~ 50°C
	Storage	-20 ~ 60°C
Humidity	Operating	0 ~ 80% Non-condensing
	Storage	5 ~ 90%, Non-condensing
Physical Properties	Material	Metal
	Weight	820g
	Dimension	168 x 99 x 60mm

Diagram

