


BE-1701A1



1-Port 17.3" LCD VGA/HDMI KVM Switch



Kvm Switch View



LCD KVM features:

No	Part	Function Description
1	Handle	Pull this handle to pull out the KVM module; push this handle to push back the KVM module.
2	LCD display	Support Auto power ON/OFF while opening & closing the monitor if there is certain degree angle ,supporting DDC/DDC2B
3	LCD control button	LCD switch button and control LCD screen position and image setting.
4	Keyboard	Support keyboard with backlight for typing comfort.
5	Touchpad	
6	LED	Power indicator
7	Rack bracket	The rack is at the two sides of the equipment, used to fix the bottom of the equipment on the rack.
8	Lock and indicating lamps	Indicating lamp of Num Lock, Caps Lock and Scroll Lock respectively.
9	Buckle	Push in this buckle before the console can be pushed and pulled freely on the rack.
10	Supports 19" rack mounting kit	

Specifications

Model No	BE-1701A1 (17.3"LCD)
Display Size	17.3"
Panel Type	SXGA TFT
Resolution Capabilities	1920x1080@60Hz
PC Port	1
USB Port	1
Best control distance	VGA/5m,HDMI/1.8m
Interface Attribute	VGA/HDMI
Keyboard	Standard 104 Keyboard
Mouse	Touchpad with two button
Angle of visibility	80/80/60/80(Typ.)(CR \geq 10)
Brightness	400 cd/m ² (Typ.)
Contrast	600:1(Typ.)
Power Consumption	15W
Power Supply	AC100~240V 50~60Hz
Operation Temperature	0°C ~50°C
Storage Temperature	-20°C ~60°C
Humidity	0~80%RH
Weight	11kg
Dimension(DxWxH)	450 * 450* 42(mm)

Ordering Information

BE-1701A1	1-Port 17.3"LCD KVM Switch
-----------	----------------------------