

# BE-1601V

## 16 ports VGA /USB KVM Switch



The BE-1601V is a 16-ports VGA /USB KVM switcher that provides a single VGA output and one mouse and keyboard to operate.

The BE-1601V can be controlled by FrontPanel

Buttons or hotkey to select the source from 16 PCs.



### Features

- ❖ 16-Ports VGA and USB KVM Switch .
- ❖ Support up to 1920x1080 resolution.
- ❖ Support usb 1.1 for keyboard and mouse.
- ❖ Control provided with front panel buttons,and Hotkey.
- ❖ Support upstream cables with VGA+USB .
- ❖ Support 19" rack mounting kit.(1U)

## Specification

Model		BE-1601V
Connectors	VGA In	16 (Female)
	VGA Out	1 (Female)
	USB Upstream	16 (to PC) by VGA+USB cable
	USB Downstream	2 (keyboard, mouse)
Input Resolution		1920x1080@60
Output Resolution		1920x1080@60
Power Supply		AC 110-220 V
Environment	Operating Temp.	0~50°C
	Storage Temp.	-20~60°C
	Humidity	20~80% Non-condensing
Physical	Housing	Metal (Black)

## Front & Rear View



## VGA+USB cable

